















Aspire 3630 Quick Spec	
Operating system¹	Genuine Windows® XP Home Edition (Service Pack 2)
Platform¹	Intel® Celeron® M processor 370/380 or higher (1 MB L2 cache, 1.50/1.60 GHz, 400 MHz FSB) SiS® M661MX chipset
System memory¹	256/512 MB of DDR333 MHz memory, upgradeable to 2 GB using two soDIMM modules
Display¹	15.4" WXGA Acer CrystalBrite™ TFT LCD, 1280 x 800 pixel resolution, supporting simultaneous multi-window viewing via Acer GridVista™ 15" XGA color TFT LCD, 1024 x 768 pixel resolution
Graphics¹	SiS® M661MX chipset with integrated 3D graphics, up to 64 MB of shared system memory, supporting dual independent display, Microsoft® DirectX® 7.0 16.7 million colors External resolution/refresh rate: <ul style="list-style-type: none"> • 2048 x 1536: 75/60 Hz • 1600 x 1200: 120/100/85/75/60 Hz • 1400 x 1050: 60 Hz • 1280 x 1024: 160/120/100/85/75/60 Hz • 1024 x 768: 200/160/120/100/85/75/60 Hz • 800 x 600: 200/160/120/100/85/75/60 Hz MPEG-2/DVD hardware-assisted capability Acer CinemaVision™ ² technology Acer ClearVision™ ² technology
Audio	Audio system with two built-in speakers Sound Blaster Pro™ and MS-Sound compatible Built-in microphone
Storage¹	40/60/80/100/120 GB ATA/100 hard disk drive
Optical media drive¹	Disk performance compatibility: <ul style="list-style-type: none"> • 8X DVD-Dual double-layer <ul style="list-style-type: none"> - Read: 24X CD-ROM, 8X DVD-R, 8X DVD+R, 4X DVD+RW, 8X DVD-ROM, 4X DVD-RW, 2.4 DL DVD+R (double-layer) - Write: 24X CD-R, 10X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD+RW, 4X DVD-RW, 2.4 DL DVD+R (double-layer) • 24X DVD/CD-RW combo

Aspire 3630 Quick Spec	
	<ul style="list-style-type: none"> - Read: 24X CD-RW, 24X CD-ROM, 24X CD-R, 8X DVD+R, 8X DVD-R, 8X DVD-ROM, 4X DVD+RW, 4X DVD-RW - Write: 24X CD-RW, 24X CD-R
Communication¹	<p>WLAN¹: Acer InviLink™ 802.11b/g Wi-Fi CERTIFIED™ solution, supporting Acer SignalUp™ wireless technology</p> <p>WPAN¹: Bluetooth® 2.0+EDR (Enhanced Data Rate)</p> <p>LAN: Fast Ethernet; Wake-on-LAN ready</p> <p>Modem: 56K ITU V.92 with PTT approval³; Wake-on-Ring ready</p>
Size and weight¹	<p>364 (W) x 279 (D) x 33.9/38.9 (H) mm (14.3 x 11 x 1.3/1.5 inches)</p> <p>2.8 kg (6.17 lbs.) for 15.4" WXGA LCD model</p> <p>2.76 kg (6.08 lbs.) for 15" XGA LCD model</p>
Power	<p>ACPI 1.0b CPU power management standard: supports Standby and Hibernation power-saving modes</p> <p>29 W 2000 mAh Li-ion battery pack (4-cell)</p> <p>1.5-hour battery life¹</p> <p>2.5-hour rapid charge system-off; 3.5-hour charge-in-use</p> <p>3-pin 65 W AC adapter</p>
Special keys and controls	<p>88-/89-key keyboard, inverted "T" cursor layout; 2.5 mm (minimum) key travel, international language support</p> <p>Touchpad with 4-way scroll button</p> <p>12 function keys, four cursor keys, two Windows® keys, hotkey controls, embedded numeric keypad</p> <p>Four easy-launch buttons: Empowering Key, email, Internet, user-programmable button</p> <p>Two front-access buttons¹: WLAN, Bluetooth®</p>
I/O ports	<p>PC Card slot (one Type II)</p> <p>Three USB 2.0 ports</p> <p>External display (VGA) port</p> <p>Headphones/speaker/line-out jack</p> <p>Microphone-in jack</p> <p>Line-in jack</p> <p>Ethernet (RJ-45) port</p> <p>Modem (RJ-11) port</p> <p>DC-in jack for AC adapter</p>
Software	<p>Acer eManager (ePresentation/eRecovery⁴/eSettings)</p> <p>Acer Arcade</p> <p>Acer GridVista™¹</p> <p>Acer Launch Manager</p>

Aspire 3630 Quick Spec	
	<p>Norton AntiVirus™</p> <p>Adobe® Reader®</p> <p>Cyberlink® PowerProducer™</p> <p>NTI CD-Maker™</p>
Optional items	<p>256/512 MB or 1 GB DDR soDIMM modules</p> <p>8-cell Li-ion battery pack</p> <p>3-pin 65 W AC adapter</p> <p>External USB floppy disk drive</p>
Warranty	<p>One-year International Travelers Warranty (ITW)</p>
           	<p>Acer recommends Windows® XP Professional.</p> <ol style="list-style-type: none"> Specifications vary depending on model and usage. Powered by CyberLink technology. PTT countries: Asia: China, Hong Kong, Japan, Korea, Malaysia, Singapore, Taiwan. Europe: Austria, Belgium, Denmark, Finland, France, Germany, Greece, Holland, Iceland, Italy, Luxembourg, Norway, Portugal, Spain, Sweden, Switzerland. Oceania: Australia, New Zealand. N. America: Canada, USA. This feature uses 2 to 3 GB of hard disk space. <p>In a continuing effort to improve the quality of our products, information in this brochure is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.</p> <p>As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.</p> <p>© 2006 Acer Inc. All rights reserved. Acer, the Acer logo and Aspire are registered trademarks of Acer Inc. Other trademarks, registered trademarks, and/or service marks, indicated or otherwise, are the property of their respective owners.</p> <p>About Acer</p> <p>Acer ranks among the world's top five branded PC vendors, designing and marketing easy, dependable IT solutions that empower people to reach their goals and enhance their lives. In 2000, Acer spun-off its manufacturing operation to focus on globally marketing its brand-name products: desktop and mobile PCs, servers and storage, displays, peripherals, and e-business solutions for business, government, education, and home users. Established in 1976, the Acer Group employs 5,600 people supporting dealers and distributors in more than 100 countries. Revenues in 2004 reached US\$7 billion. Please visit www.acer.com.</p>